Installation Engineers Contact Details: Luminaire Ref / Loca							Locatio	n			
Name:			Tel:								
Luminaire Details:			Full Recharge Duration 24H			Hours	lours Duration: 3hrs			Lamp Type:	
ROUTINE TEST RECORD											
Test Type	Year 1		Year 2		Year 3		Year 4		Year 5		
	Signed	Date	Signed	Date	Signed	Date	Signed	Date	Signed	Date	
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
3hr Duration											

Dimensions:

Part No.	Description	L (mm)	W (mm)	H (mm)	Weight
430196	Hurworth 3CCT Wallpack	310	265	122	2.1Kg



Installation Instructions



Hurworth 3CCT Wallpack

Input	220-240V AC 50/60Hz
Power	30W
Operating Temp	-20-+30°C, 0-+30°C (Emergency)
Connection Type	Screw Terminal
Emergency Option	Available
Control Connection	Available



Box Contents:

Hurworth Bulkhead

Light Source Energy Rating F

Fixings



Replaceable



Replaceable







Protection

Tools Required For Installation:

- Screwdriver
- Drill





READ THESE INSTRUCTIONS THOROUGHLY BEFORE INSTALLATION KEEP THESE INSTRUCTIONS FOR FUTURE REFERENCE. **IMPORTANT:**

This product must be installed by a qualified electrician or competent person, and in accordance with current building and IET wiring regulations.

Warranty:

This luminaire is warranted for a period of 5 Years from the date of purchase**. The backup battery pack in the emergency version is warranted for a period of 5 Years. The warranty could be invalidated should the light fitting not be installed according to these instructions, outside the scope of the specification or the product has been altered or tampered with in any way. Please see website for terms and conditions.



Disassembly instructions for end of life disposal available on website.

Disposal of Electronic Equipment WEEE Directive 2002/96/EC This product falls within the scope of the Waste Electrical & Electronic Equipment Directive (WEEE), which means the product should not be disposed of as normal household waste. Please recycle where facilities exist or check with your Local Authority. RoHS - All components and materials used in this product are RoHS 2002/95/EC compliant. Specifications may change from time to time. The information contained in this leaflet is for guidance only and should not be considered as always accurate and should be treated as not representative.







WARNING: Risk of electric shock! Isolate the mains power before proceeding.

- Turn off the mains power before performing inspections, installation, or removal
- Verify that the supply voltage is correct by comparing it with the luminaire label information
- It is the installers responsibility to ensure installation is suitable for the total load of the luminaire(s). The supply cable, fuses/circuit brakers must be correctly rated for the electrical load and considering for any transient inrush currents that may occur.
- Do not perform insulation strength or resistance tests on installed luminaire(s) connected

Wiring instructions for units equipped an with EMERGENCY function:

Emergency lighting luminaries must be installed and maintained in accordance with the emergency lighting standard BS 5266-1

- For the emergency unit to work correctly, please ensure that an uninterrupted permanent live feed is present and is connected directly to the 'Permanent Live' terminal of the mains terminal block. Please ensure there are no switches, PIRs etc within the permanent live feed, constant switching of the emergency pack could result in premature battery failure.
- Following power up the green LED indicator should illuminate to indicate charging. If power to the unit is disrupted or isolated, the unit indicating green LED will switch off, triggering the emergency LEDs to illuminate.
- When self-test mode is selected, 24hrs from connection to mains power, a 3hrs duration test will be performed automatically.

Installation Procedure:

- 1. Isolate Power, Unscrew the 7 screws securing the diffuser.
- 2. Drill the required mounting points in the base, mark and drill holes into the mounting surface.
- 3. Secure the fixture in place. Note: if protection against ingress of moisture is required, the head of screws must be covered with a water resistant sealant.
- 4. Install the supplied cable gland to required position.
- 5. Tighten the cable gland.
 Thread cable through gland and wire as per diagram below.
- 6. Connect Battery (Emergency versions only)
- 7. Secure diffuser into position.
- B. Reconnect the mains supply.



