GRAFHAM HIGH BAY

Grafham 5W E-SEL3 High Bay Emergency Conversion Pack 20-30V DC 250mA LifePO4 6.4V DC 4.5Ah Plug & Play



Grafham 5W E-SEL3 High Bay Emergency Conversion Pack 20-30V DC 250mA LifePO4 6.4V DC 4.5Ah Plug & Play

Product code **431430**

Power	**5W**
Emergency duration	**3 h**
Supply voltage	**220-240V AC**
Protection	**IP20 · IK03**
Warranty	**5 years**

Features

- High Bay Plug & Play Emergency pack
- Selectable Emergency

Certification and options



Specification

Electrical

Power	**5W**
Supply voltage	**220-240V AC**
Frequency	**50 Hz / 60 Hz**

Lifetime and warranty

Warranty	**5 years**
Replaceable driver	**No**
Replaceable light source	**No**

Construction

Ingress protection	**IP20**
Impact resistance	**IK03**
Body	**Polycarbonate**
Colour (RAL)	**RAL 9011**
Location	**Internal**
Dimensions (L x W x H)	**190 x 190 x 53 mm**
Weight	**0.77 kg**

Installation

Mounting	**BESA/Conduit**
Connection	**Flying Lead**
Ambient temperature	**0 to +30 °C**

Emergency

Battery discharge	**100 mA**
Battery length (mm)	**135**
Battery temperature, max. (°C)	**60**
Battery width (mm)	**27**
Battery capacity	**3,600 mAh**
Cell type	**YH IFR18650 - LiFePO4**
Charge current	**250 mA**
Duration	**3 h**
Mode	**Maintained/Non-Maintained**
Recharge time	**24 h**

Values are nominal. Specifications may change without notice; the product page always carries the latest version.

Compatible modules and accessories

	CODE	DESCRIPTION
	421363	Brackets for Emergency Conversion with 430964 (Netherton P&P) Pair

DOWNLOADS

Photometric files (LDT), installation instructions and the latest datasheet are on the product page:

www.lumineux.co.uk/shop/431430-grafham-5w-e-sel3-high-bay-emergency-conversion-pack-20-30v-dc-250ma-lifepo4-6-4v-dc-4-5ah-plug-play-61614

WARRANTY AND SUPPORT

5 years warranty. Terms at www.lumineux.co.uk/product-warranty-on-site-warranty.

Free lighting design and technical support: 01507 328031, support@lumineux.co.uk