

Technical Specification

Category: Grafham High Bay


Part Number: 430965-R2

Description: Grafham 4W E-SEL3 High Bay Emergency Conversion Pack 20-55V DC 100mA LifePO4 6.4V DC 3.6Ah Plug & Play with Jack Leads



Product Features:

- High Bay Plug & Play Emergency pack
- Selectable Emergency



General information:

Wattage (W)	4
IP Rating	20
IK Rating	3
Paint Finish (RAL)	9003

Technical information:

Application Location	Internal
Input Type	220-240V AC
Operating Temperature To	30
Product Warranty (Years)	5
Driver Brand	Lumineux
Socket	N/A
Frequency (Hz)	50 60
Install Options	BESA/Conduit
Install Type	Flying Lead
Replaceable Driver	Professional
Replaceable LED	Professional
Body Material	Polycarbonate
Maintained	Maintained/Non-Maintained
Emergency Wattage (W)	4.0
Emergency IP Rating	65
Cell Type	YH IFR18650 - LiFePO4
Capacity (mAh)	3600
Recharge Time (Hours)	24
Emergency Duration (Hours)	3
Charge Current (mA)	250
Battery Size (V/Ah)	6.4 / 3.6
Battery Temperature (To) (°C)	30
Module Length (mm)	276
Module Width (mm)	110
Module Height (mm)	56
Battery Length (mm)	1350
Battery Width (mm)	27

Technical Specification

Category: Grafham High Bay

Part Number: 430965-R2

Description: Grafham 4W E-SEL3 High Bay Emergency Conversion
Pack 20-55V DC 100mA LifePO4 6.4V DC 3.6Ah Plug & Play with
Jack Leads



Technical information:

Battery Height (mm)	27
Battery Discharge (mA)	100
Sensor Technology	Microwave