

# Technical Specification



**Category:** Foremark Single Wattage


**Part Number:** 430733-90

**Description:** Foremark High Bay 100W 5000K IP65 90D Plug & Play (Zhaga)



## Product Features:

- Supplied with 1.5M prewired H05RN-F cable
- Sosen LED Driver
- 90° or 120° optic options
- Plug & Play Enabled – Sensors and Emergency




## General information:


Wattage (W)	100
Lumens (lm)	14500
Efficacy (lm/W)	145
Beam Angle	90
CRI	80
Colour Temperature (K)	5000
Operating Temperature From	-30
Operating Temperature To	50
Application Location	Internal

## Technical information:

Class Rating	1
Input Type	120-240V AC
IP Rating	65
IK Rating	8
L70 Hours	60000
L80 Hours	0
L90 Hours	0
Product Warranty (Years)	5
SDCM	0
Surge (kV)	6 L-N   6 L / N-G



**100W:**  
177mm  
**150W:**  
177mm  
**200W:**  
187mm



**100W:**  
304mm  
**150W:**  
304mm  
**200W:**  
315mm

# Technical Specification

**Category:** Foremark Single Wattage

**Part Number:** 430733-90

**Description:** Foremark High Bay 100W 5000K IP65 90D Plug & Play (Zhaga)



## Compatible Products:



401754

Alwen PIR Highbay Remote



430569

Alwen Plug & Play 12V Microwave Sensor 12M Black (Zhaga)



430568

Alwen Plug & Play 12V PIR Sensor Black (Zhaga)



401063

Foremark (All Wattages) & Meadley 200W PC Diffuser With Cover



430341

Foremark Adjustable Bracket 3 Part



430965-R2

Grafham 4W E-SEL3 High Bay Emergency Conversion Pack 20-55V DC 100mA LifePO4 6.4V DC 3.6Ah Plug & Play with Jack Leads



431173

Universal High Bay Rotatable Bracket



430625

truSmart Crown Zhaga Plug & Play 12V PIR Sensor Black