

Belmont

Category: Belmont


Part Number: 431191-85

Description: Belmont Linear High Bay 100W/120W/150W 5000K
IP66 Grey 85D



Product Features:

- Fresnel optics for improved glare control
- Tough, impact resistant IK10 housing
- Plug & Play Enabled – Sensors and Emergency



General information:

Wattage (W)	100 / 120 / 150
Lumens (lm)	18,000 / 21,600 / 27,000
Efficacy (lm/W)	180
Colour Temperature (K)	5000
IP Rating	66
IK Rating	10
Class Rating	1
Dimmable	0-10V
L70 Hours	50000
Paint Finish (RAL)	9006

Technical information:




Application Location	Internal
Emergency Output (lm)	700
Beam Angle	85
Optics	Symmetric
CRI	80
Input Type	220-240V AC
Driver Type	CC
Operating Temperature From	-30
Operating Temperature To	50
Product Warranty (Years)	5
Driver Brand	DONE
Socket	Zhaga
Frequency (Hz)	50 60
Diffuser Material	Polycarbonate
Install Options	BESA/Conduit
Install Type	1.5m H05RN-F
Replaceable Driver	Professional
Replaceable LED	Professional
Body Material	Aluminium

Belmont

Category: Belmont

Part Number: 431191-85

Description: Belmont Linear High Bay 100W/120W/150W 5000K
IP66 Grey 85D



Compatible Products:



401754

Alwen PIR Highbay Remote



430569

Alwen Plug & Play 12V
Microwave Sensor 12M Black
(Zhaga)



430568

Alwen Plug & Play 12V PIR
Sensor 12M Black (Zhaga)



430243

Belmont +/- 60D Rotatable
Bracket (Pair)



430964

Grafham 4W E-SEL3 Linear
High Bay Emergency
Conversion Pack 20-55V DC
100mA LifePO4 6.4V DC
3.3Ah Plug & Play



430625

truSmart Crown Zhaga Plug &
Play 12V PIR Sensor Black