

# Technical Specification

**Category:** Meadley New


**Part Number:** 431333-120

**Description:** Meadley High Bay 200W 5000K IP65 Plug & Play 120D



## Product Features:

- Supplied with 1M prewired HO5RN-F cable
- Lifud LED driver
- IP65 & IK08 Rated
- 90° or 120° optic options
- Plug & Play Enabled – Sensors and Emergency
- 5 Year Product Warranty
- 160 lm/W



## General information:

Wattage (W)	200
Lumens (lm)	32,000
Efficacy (lm/W)	160
Colour Temperature (K)	5000
IP Rating	65
IK Rating	8
Class Rating	1
Energy Rating	C
Flicker	Flicker Free
Dimmable	truSmart
L70 Hours	170000
L80 Hours	110000
L90 Hours	51000
Paint Finish (RAL)	9017

## Technical information:

Application Location	Internal
Emergency Output (lm)	650
Beam Angle	120
Optics	Symmetric
CRI	70
Input Type	220-240V AC
Driver Type	CC
Operating Temperature From	-30
Operating Temperature To	50
Product Warranty (Years)	5
SDCM	5
Driver Brand	Lifud
Socket	Zhaga
Frequency (Hz)	50   60
Diffuser Material	Polycarbonate
Install Options	BESA/Conduit
Install Type	1.0m H05RN-F
Replaceable Driver	Professional
Replaceable LED	Professional
Body Material	Aluminium

# Technical Specification

**Category:** Meadley New

**Part Number:** 431333-120

**Description:** Meadley High Bay 200W 5000K IP65 Plug & Play 120D



## Compatible Products:



401754

Alwen PIR Highbay Remote



430569

Alwen Plug & Play 12V  
Microwave Sensor 12M Black  
(Zhaga)



430568

Alwen Plug & Play 12V PIR  
Sensor Black (Zhaga)



431206

Alwen Zhaga Plug & Play PIR  
Sensor 16M



430965

Grafham 4W E-SEL3 High Bay  
Emergency Conversion Pack  
20-55V DC 100mA LifePO4  
6.4V DC 3.6Ah Plug & Play



431430

Grafham 5W E-SEL3 High Bay  
Emergency Conversion Pack  
20-30V DC 250mA LifePO4  
6.4V DC 4.5Ah Plug & Play



430625

truSmart Crown Zhaga Plug &  
Play 12V PIR Sensor Black