

# Tempest Anti-Corrosive

**Category:** Tempest

**Part Number:** 431343-E3

**Description:** Tempest Anti-Corrosive 5ft Twin 70W 5000K IP65 Grey  
Plug & Play High Output E-SEL3 Emergency



## Product Features:

- Opal Diffuser
- Pre-threaded M20 cable entry
- Designed for easy and rapid installation



## General information:

Wattage (W)	70
Lumens (lm)	12600
Efficacy (lm/W)	180
Colour Temperature (K)	5000
IP Rating	65
IK Rating	8
Class Rating	1
Energy Rating	A
Flicker	Flicker Free
Dimmable	Fixed
L70 Hours	70000
Paint Finish (RAL)	7047

## Technical information:

Application Location	Internal
Beam Angle	120
CRI	80
Input Type	220-240V AC
Driver Type	CC
Operating Temperature From	-20
Operating Temperature To	45
Product Warranty (Years)	5
Driver Brand	Boke
Socket	N/A
Frequency (Hz)	50   60
Diffuser Material	Polycarbonate
Install Options	BESA/Conduit
Install Type	Push Fit Terminal
Replaceable Driver	Professional
Replaceable LED	Professional
Body Material	Polycarbonate
Maintained	Maintained/Non-Maintained
Emergency Wattage (W)	2.5

# Tempest Anti-Corrosive

**Category:** Tempest


**Part Number:** 431343-E3

**Description:** Tempest Anti-Corrosive 5ft Twin 70W 5000K IP65 Grey  
Plug & Play High Output E-SEL3 Emergency



## Technical information:

Emergency IP Rating	20
Cell Type	YH IFR18650 - LiFePO4
Capacity (mAh)	3200
Recharge Time (Hours)	24
Emergency Duration (Hours)	3
Charge Current (mA)	250
Battery Size (V/Ah)	3.2
Battery Temperature (To) (°C)	30
Module Length (mm)	170
Module Width (mm)	54
Module Height (mm)	32
Battery Length (mm)	1300
Battery Width (mm)	20
Battery Height (mm)	20
Battery Discharge (mA)	130



# Tempest Anti-Corrosive

**Category:** Tempest

**Part Number:** 431343-E3

**Description:** Tempest Anti-Corrosive 5ft Twin 70W 5000K IP65 Grey  
Plug & Play High Output E-SEL3 Emergency



## Compatible Products:



431346

Alwen Linear Microwave/SD  
Sensor 12V DC Plug & Play

430962

Grafham 3.5W Conversion  
Pack 50-300V DC 0-40mA  
LifePO4 3.2V DC 3.2Ah Plug &  
Play E-SEL3 Emergency

430904

Step-Dim Remote Control for  
431346