

Derwent

Category: Derwent


Part Number: 431175-85

Description: Derwent Mid Bay 75W/95W/118W 5000K Grey IP65 85D



Product Features:

- Wattage selectable (3 options)
- Highly efficient – 180 lm/W
- Suspension kit included
- Sleek, compact design
- Plug & Play Enabled – Sensors and Emergency



General information:

Wattage (W)	75 / 95 / 118
Lumens (lm)	13,500 / 17,100 / 21,250
Efficacy (lm/W)	180
Colour Temperature (K)	5000
IP Rating	65
IK Rating	8
Class Rating	1
Energy Rating	A
Dimmable	0-10V / truSmart
L70 Hours	60000
Paint Finish (RAL)	9006

Technical information:



Application Location	Internal
Emergency Output (lm)	650
Beam Angle	85
Optics	Symmetric
CRI	80
Input Type	100-240V AC
Driver Type	CC
Operating Temperature From	-30
Operating Temperature To	50
Product Warranty (Years)	5
Driver Brand	Sosen
Socket	Zhaga
Frequency (Hz)	50 60
Diffuser Material	Polycarbonate
Install Options	BESA/Conduit
Install Type	1.5m H05RN-F
Replaceable Driver	Professional
Replaceable LED	Professional
Body Material	Aluminium
Maintained	Maintained/Non-Maintained
Sensor Technology	Microwave

Derwent

Category: Derwent

Part Number: 431175-85

Description: Derwent Mid Bay 75W/95W/118W 5000K Grey IP65
85D



Compatible Products:



401754

Alwen PIR Highbay Remote



430569

Alwen Plug & Play 12V
Microwave Sensor 12M Black
(Zhaga)



430568

Alwen Plug & Play 12V PIR
Sensor Black (Zhaga)



431206

Alwen Zhaga Plug & Play PIR
Sensor 16M



Image Coming Soon

431176

Derwent Mid Bay Adjustable 3
Part Bracket



Image Coming Soon

431174

Derwent Mid Bay Emergency
Mount Bracket Pair



430964

Grafham 4W E-SEL3 Linear
High Bay Emergency
Conversion Pack 20-55V DC
100mA LifePO4 6.4V DC
3.3Ah Plug & Play



431431

Grafham 5W E-SEL3 Linear
High Bay Emergency
Conversion Pack 20-30V DC
250mA LifePO4 6.4V DC
4.5Ah Plug and Play

Derwent

Category: Derwent

Part Number: 431175-85

Description: Derwent Mid Bay 75W/95W/118W 5000K Grey IP65
85D



430625

truSmart Crown Zhaga Plug &
Play 12V PIR Sensor Black